

# Control your destiny.

The Aria Forte DMX Transmitter



## Features

- Control lights in up to 8 independent banks
- Half mile line of sight range
- Frequency hopping spread-spectrum radio ensures reliable transmission
- Manual brightness control enables performances where no DMX is available
- Status indicator shows transmissions for easy diagnostics
- Two diagnostic patterns for rapid set up
- Works with all Aria Forte Orchestra (F2O) lights
- Uses 900Mhz band which avoids wireless audio
- FCC and ISED certification means no license is required
- Eight unique channels allows multiple nearby installations
- USB-powered to allow battery operation for run out concerts
- Low power consumption
- USB power adapter and nine-foot (2.75m) USB cord included

## Specifications

Model	FDMX1
Frequency Range	902-928MHz
Spread-spectrum channels	50
Power supply	5VDC at 2A
Typical power consumption	0.5W
Certifications	FCC, ISED
Case material	powder-coated aluminum
Cord length	9 ft (2.75 m)
Case dimensions	3.4 in. (86 mm) w, 3.3 in. (85 mm) l, 1.6 in. (40 mm) t
Antenna dimensions	7.6 in. (195 mm) w, 0.35 in. (9 mm) diameter
Weight	5.3 oz (150 g)



Get complete freedom on your stage or pit with the Aria Forte DMX Transmitter. Wirelessly control any number of Aria Forte Orchestra lights from your lighting console with full dimming. Do blackouts, set the mood, or feature one section of the orchestra . . . all without a single wire on the stage. You're really in control now.

**Bold. Bright. Beautiful. Aria Forte.**

